



118-137 MHz User Tunable VHF Filter



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

Part Number: AE118-137TB110

Electrical Specifications

Tuning Frequency Range: 118-137 MHz
Insertion Loss @ Fc (within tuned frequencies 118-137 MHz): 1.2 dB Max
Return Loss @ Fc (within tuned frequencies 118-137 MHz): 13 dB Min
Attenuation: Out-of-band attenuation, at ± 2.2 MHz from tuned frequency: ≥ 12 dB

Mechanical

Connector Type: TNC (F)
Dimensions: 13.59 x 3.25 x 1.83 Inches

Environmental

Operating Temperature: -40 to +85° C

Outline Drawing:

