



105-115 MHz User Tunable VHF Filter

Part Number: AE105-115TB108

ANATECH ELECTRONICS INC
RF & Microwave Filters & Products



Electrical Specifications

Tuning Frequency Range: 105-115 MHz
Insertion Loss @ Fc (within tuned frequencies 105-115 MHz): 1.2 dB Max
Return Loss @ Fc (within tuned frequencies 105-115 MHz): 13 dB Min
Attenuation: Out-of-band attenuation, at ± 2.2 MHz from tuned frequency: ≥ 12 dB

Mechanical

Connector Type: TNC (F)
Dimensions: 13.59 x 3.25 x 1.83 Inches

Environmental

Operating Temperature: -40 to +85° C

Outline Drawing:

