



1850MHz Bandpass Filter

P/N AE1850B6731

Electrical Specifications

| | |
|--------------------------|------------|
| Center Frequency (Fo): | 1850MHz |
| 1dB Bandwidth: | 370MHz Min |
| Ripple in Bandwidth | <0.1dB |
| Return Loss in Bandwidth | >14dB |
| Insertion Loss @ 1850MHz | <1.5dB |
| Rejection @ 0-1470MHz | >60dB |
| Rejection @ 2230-4000MHz | >60dB |
| Power | 10 W |
| Connector Type | SMA |

Outline Drawing

