



1600.0 MHz SAW Bandpass Filter

Part Number: AM1600S1059

Center Frequency (= Fc)	1600.0 MHz
Pass Bandwidth	1550.0-1650.0 MHz
Insertion Loss (in B.W)	4.0 dB max.
Ripple (in B.W)	Max 1.0
Return Loss (dB) in B.W	Min.14.0
In, Output Impedance	50 Ω
Attenuation	1) min 35dB @1700 ~ 1800 MHz 2) min 45dB @1200 ~ 1500 MHz
Input Power	3 Watt max.
Operation Temperature Range	- 40 to +85 deg. C

Specification: base on @ 25 deg. C

Outline Drawing:

